

PDM: Rev:K

STATUS: Released

Printed: Dec 20, 2010

4 1|2 3 PRODUCT NUMBER LENGTH FORMULAS (SEE NOTE 10) DIM 51762-ABBCCCOOEF__ DIM "A" 100 [2.54] x (CCC/4) + .250 [6.35] x BB + .650 [16.51] (NOTE 10) Note: (3) DIM "B" 100 [2.54] x (CCC/4) + .250 [6.35] x BB + .350 [8.89] SEE NOTE I DIM "C" 100 [2.54] x (CCC/4) + .250 [6.35] x BB + .300 [7.62] DIM "E" 100 [2.54] x (CCC/4) + .450 [11.43] DIM "F" 100 [2.54] x (CCC/4) + .250 [6.35] x BB + .680 [17.27] DIM "H" 100 [2.54] x (CCC/4) + .250 [6.35] CONNECTOR NOTES

PRODUCT NUMBER CODE:

51762 - A BB CCC 00 E F LF

NO THIS SUFFIX:100u"/2.54um Snpb ON PCB INTERFACE
ADD THIS SUFFIX:18u"/2.00um Sn ON PCB INTERFACE
RETENTION TO PCB (NOTE 8)
TAIL OPTIONS (NOTE 7)
ALWAYS '00' (ZERO, ZERO) (NOTE 6)
NUMBER OF SIGNAL CONTACTS (NOTE 5)
PLATING (NOTE 3)]
BASE NUMBER
BASE NUMBER

2. HOUSING MATERIAL: GLASS FILLED V-O HIGH TEMP THERMO PLASTIC.
SIGNAL CONTACT MATERIAL: COPPER ALLOY
POWER CONTACT MATERIAL: COPPER ALLOY

PLATING OPTION: | | = SEE PRINT | 10064183 FOR PLATING SPEC OF 51762-1BBCCC00EF; 51762-1BBCCC00EFLF

4. RIGHT END POWER CONTACTS, 01 TO 19 AVAILABLE.
MAXIMUM OF 20 POWER CONTACTS PER CONNECTOR

5. SIGNAL CONTACTS, 004 TO 148 AVAILABLE FOR SOLDER TO BOARD.
020 TO 148 AVAILABLE FOR PRESS-FIT TO BOARD.

THIS FILE WAS ORIGINALLY CREATED IN THE PRO

ENGINEER ENVIRONMENT AND ANY FUTURE REVISIONS TO THIS FILE MUST BE MADE IN THE PRO ENGINEER

6. THIS PART NOT AVAILABLE WITH LEFT SIDE POWER CONTACTS.

7. TAIL OPTIONS: A = .135 ±.010 [3.43 ±.25] SOLDER TO BOARD B = .090 +.005 / -.010 [2.29 +0.13 / -0.25] SOLDER TO BOARD C = .154 ±.010 [3.91 ±0.25] PRESS-FIT TO BOARD 8. RETENTION TO PCB OPTIONS:
A = BOARD LOCK (REQUIRES .098 +.002/-.001
[2.49 +0.05/-0.03] THRU HOLE IN PCB
MOUNTING FOOT HEIGHT:
.220[5.59]
NOT AVAILABLE FOR PRESS-FIT
B = .150 [3.81] THRU HOLE (REQUIRES .158 ±0.0

B = .150 (3.81) THRU HOLE (REQUIRES .158 ±0.003 (4.01 ±0.08) THRU HOLE IN PCB).
MOUNTING FOOT HEIGHT .160(4.06)

9. MANUFACTURE'S NAME, P/N, AND DATE CODE

TO APPEAR ON THIS SURFACE.

(10) THE MAXIMUM OVERALL LENGTH (DIM A) OF A PART

IS 8.00 [203.2]
II. PRODUCT SPECIFICATION GS-12-149

12. APPLICATION SPECIFICATION BUS-20-067. 13. FOR PRESS-FIT CONNECTORS USE FCI CAM TOOL 430140-XXX TO APPLY CONNECTOR TO PCB.

PCB NOTES:

14. ALL DIMENSIONS ARE BASIC UNLESS OTHERWISE SPECIFIED.

15. ALL THROUGH HOLES ARE LOCATED WITH A

TRUE POSITION OF .004[0.10]

(17) Ø 0.0453 ±.001 [1.151 ±0.02] DRILLED HOLES PLATED WITH 0.0003 [0.007] MIN SnPb OVER 0.001 [1.03] TO .003 [0.08] PLATING TO ACHIEVE A .040±.003 [1.02±08] HOLE.

18. A SYMBOL WILL BE NEXT TO ANY DIMENSION, VIEW, OR NOTE
WHICH HAS BEEN MODIFIED WITH THE CURRENT DRAWING REVISION

mat'l code						tolerances unless otherwise specified					CUSTOMER				F	<u>C</u>	ı				
Itr	ecn	ecn no. dr		do	ite		.XX±.01/.X±.3			COPY			www.fciconnect.com								
К						linear	.XXX±.005/.XX±.13				projection			title	le IGHT ANGLE RECEPTACLE w/GUIDE PIN						
							.XXXX±.0020/.XXX±.051			41			KIGH	OHI ANGLE RECEPTACLE W/GUIDE PIN I POWER / SIGNAL							
						angles	0°±2°			W U		FOWER / STONAL									
						dr	D.BOGLE		05-I	8-99	INC	⊔ / M	MM	produ	product fam		PWRBLADE		code		
						engr	J. BROWN 05-18		8-99	11110			size	dwg					213		
						chr	J. BROWN		05-18-99		scale :		Λ	51762				SHEET			
					appd	appd J. BROWN		05-18-99		1.1			\vdash					2 0	2 OF 3		
sh	eet	revisi	on																		
index		sheet																			

form no. 7530-001-103

LENVIRONMENT

1 2

PDM: Rev:K

3

22526

cage code

В

Α

